



RIO

FESTIVA

60W WIRELESS DMX

BW

RoHS
Compliant

FESTIVA BW :

The FESTIVA Wireless, Battery operated LED RGBW light is perfect for mobile lighting applications. These lights are extremely easy to set up and can be used with full DMX capabilities.

BATTERY POWERED

The FESTIVA lights can be powered via the built in battery which can last up to 18 hours on a single charge! These lights are charged with the provided IEC cord or can be left plugged in for longer running applications.

WIRELESS OPERATION

DMX signal can be sent wirelessly with the optional DMX signal transmitter. You can then use a DMX512 Spectrum Select controller to control the lights without using any DMX cable. You can also connect an DMX XLR cable to the lights to operate them as well. Additionally, you can connect to the first fixture with a XLR cable and use that first fixture to talk wirelessly to the rest of the BW Lights in the system.

BUILT IN MODES

You can also use the BW Festiva lights with the built in color change modes, or select a static color from the built in LCD screen. The FESTIVA lights also come with a Sound Activated function that with an onboard Mic will pick up sounds and change the lights colors along to the music.

ORDERING GUIDE

Part # **BW-610-B**

Housing	Die-cast aluminum	
Wattage	60W	
Control Type	DMX 512, Auto Run, Master/Slave, Sound Activated	
Voltage	AC90V-250V, 50-60HZ	
LED Type	6x10W RGBW 4-in-1	
Beam Spread	10°	
Battery Life	Full Color	5 hours
	Color Fade / 100%	8 hours
	Color Fade / 75%	13 hours
	Color Fade / 50%	18 hours

CHARGING FLIGHT CASE

An optional flight case is also available to house 8 BW-610-B fixtures. The lights can be plugged into the case, and the case can then be plugged into a wall, quickly and easily charging all 8 lights at once! Comes in either 9mm or 12mm thick wood.

