



Smart led lamps

RGBW
GEMINIv2
2w

G4



G4 2W LED:

IFX's GEMINI Bluetooth controlled RGBW LED G4 lamp is an innovative LED product for many lighting applications. Use the free Bluetooth enabled Smartphone or tablet APP to control 1 or more lamps.


You can select colors or 2700K white. You can also dim your lights and create schedules for automatic lighting control.

- iOS (10.0 and above) and Android (4.4.4 and above) compatible
- Works on a Bluetooth MESH network

SPECIFICATIONS

| | | |
|----------------|---------------------------------|--------|
| Type | G4 | |
| Wattage | 2W | |
| Voltage | 12V AC/DC | |
| Color Temp | RGBW 2700K | |
| Base | G4 | |
| Power Factor | 12VDC 1.0, 12VAC 0.6 | |
| Lumens | 2700K (WW) | 120 Lm |
| | Red | 18 Lm |
| | Green | 42 Lm |
| | Blue | 11 Lm |
| Beam Angle | 360 | |
| Operating Temp | -4°F-104°F | |
| Life | 25,000 Hours | |
| Dimmable | Yes - Via smartphone/tablet APP | |
| Environment | Suitable for dry locations | |
| Certifications | ErP, RoHS, CE, FCC | |
| Warranty | 3 years | |

DIMENSIONS



ORDERING GUIDE

example product code: G4/02/OM360/RGB27-BT

| LIGHT SOURCE | WATTAGE | LED | BEAM SPREAD | COLOR TEMP | WIRE LESS |
|--------------|---------|-----|-------------|------------|-----------|
| G4 Wafer | 2 | SMD | OMNI360 | RGBW27 | BT |

RELATED ACCESSORIES

Bluetooth WiFi Gateway BTMG



A Gateway is needed to bridge the Bluetooth lamps to the WiFi network and allow control over the internet

Bluetooth Mesh Repeater BMR01



The BT Mesh Repeater enhances the Bluetooth signal and helps the signal penetrate materials to improve performance

MR16



RGBW G4 Wafer



SCAN TO DOWNLOAD APP

Apple

Android

