



12V AC

TR-RK ROCK

300/600W

TR



ROCK TR-RK :

The TR-RK series 12VAC "Real Rock" low voltage transformers are a perfect solution for a natural looking transformer to blend in with the surroundings of a landscape. Multi-tap 12-15vAC outputs allow for easy installation of multiple lighting fixtures at varying distances.

- Standard mandatory secondary protection
- Comes standard with 6' power cord attached. Single gang junction box available upon request
- Meets or exceeds UL, cUL, ANSI/UL, and CSA requirements

SPECIFICATIONS

	TR-RK-300	TR-RK-600
Output Voltage	12-15VAC-25A Max	12-15VAC-50A Max
Input Voltage	120VAC-3A Max	120VAC-6A Max
Breakers	1x25A	2x25A
Frequency	60 Hz	
Dimensions (LxWxH)	19" x 14" x 12"	24" x 12" x 12.5"
Weight	13 LBS	17 LBS
Dimmable	Yes — With low-voltage magnetic dimmer	

Model Number	Output Voltage	Max Load	Input Voltage	Material	Dimensions	Weight
TR-RK-300	12-15VAC	300W	120VAC	RealRock	19" x 14" x 12"	13 LBS
TR-RK-600	12-15VAC	600W	120VAC	RealRock	24" x 12" x 12.5"	17 LBS